

## **BALER DIVORCE: EMERGENCY PROCEDURE**

v. 2014.034 DC, NB

B14 BALER NOTE: If you get stuck in the field with a B14 Baler that the Q330 cannot connect to because the B14 Baler hasn't had its association cleared there is an emergency procedure to be used only in the field AND when you do not have another spare B14.

1. Power B14 (manual says do not have the q330 connected but I WAS successful with a q330 connected).
2. Right away after seeing the status idle light on hold down the B14 Baler ATTN button until the light on the baler goes solid red, approximately 5 seconds then release the button.
3. Wait until the light starts flashing green and then shut down the Baler by pressing the ATTN button just once.
4. Once it has returned back to its sleep idle state (status light flashing green every 5 seconds) then...
5. Repeat steps 2-4 (be patient the B14 OS is not fast!)
6. Now go to your Clie and or Willard and turn on the Baler and watch to see that the packets are being sent to the B14. (Willard: Commands ->Baler Control -> click Serial 2 radio button -> click Turn On Baler ) (Clie: Commands -> Baler Cmds -> Send Baler Command, then after the Baler boots Clie: Status ->Data Port Txfr -> Data4 Packet Buffer decreases to zero)

### **Attention:**

This does not clear any pre-existing data, you may not have enough space on the B14 if it has too much pre-existing data on it.