

## **USING BALEADDR :: EMERGENCY PROCEDURE**

Plug in baler download cable to power, baler, and Ethernet into the laptop.

Check that the laptop is set to a private IP and wireless is off. The baleaddr program should be in the Q330Programs package on all of the PIC laptops. Run baleaddr from the icons on the Mac dock or from X11 window running wine. The program itself lives in /Users/field/.Q330\_programs (use ls -A to find it)

Set IP in the baleaddr GUI to 192.168.0.2 (or similar IP for the private IP network on the laptop)

Push the ATTN button, the link led should light when the baler starts booting otherwise there is a wiring problem.

When the baler is done booting the GUI will show a connection to the baler and fill in the information, if the baler forgets what serial number it is and never returns a baler ok line in the console part of the GUI, then the baler is non-functional and needs to be returned to the PIC, otherwise it's ok.

Use BLINE or the Web Browser Method to download the data from the baler.

Web Browser Method:

Use the ip of the baler that baleaddr has assigned (from above), in this case 192.168.0.2 to connect using a web browser like Safari, Firefox, etc.

Navigate to the data retrieval page and put ??-??? in "Seed Name(s)" and click the download button and it will download all of the data into a concatenated file (look in the Downloads folder) with a naming convention of something like C123456789123\_EDIT.xxx (12 letters/numbers - underscore - station name - dot - xxx). Use baleaddr GUI to select "Clean Baler" to clear the association destroy the data on the baler...then it will reconnect to a new Q330.